

Table 2-24 Printer maintenance menu (continued)

| Menu item | Sub-menu item | Description |
|--------------------------------|-----------------------------|--|
| | | <p>On: The printer reprints any page involved in a jam. Additional memory is allocated to store the last few pages printed. This might cause overall printer performance to suffer.</p> <p>Off: The printer does not reprint any page that was involved in a paper jam. Because no memory is used to store the most recent pages, performance is optimal.</p> |
| Less Paper Curl | On | When printed pages are consistently curled, this option sets the printer to a mode that reduces curl. Use the slider icon to enable or disable this feature. |
| Troubleshooting | Event Logs | <p>Prints a list of the last 50 events and errors that happened on the printer.</p> <p>This will show a list on the display of the event logs. On a touch screen display, there is also an option to print the list of events.</p> <p>On 2-line displays, there are two menu options:</p> <ul style="list-style-type: none">• Print All• Event Log List |
| Troubleshooting (continued) | Fax | <p>Print Fax Trace</p> <p>Prints a fax trace.</p> <p>NOTE: Only available on the fax models.</p> |
| Update the Printer | | <p>If selecting Update the Printer allows the user to do the following:</p> <ul style="list-style-type: none">• Check for Printer Update Now• Printer Update Options allows the user to turn Auto Update Off or On.• Manage Updates <p>Allows updates Yes or NO and or Allow Downgrades Yes or No.</p> |
| Restore | Restore Network Settings | Resets all network configurations to their factory defaults. |
| | Restore Factory Defaults | Resets all settings to factory defaults values. |
| | Cold Reset | Resets all settings to factory defaults values. |
| | Printer Supply Region Reset | <p>There are three regional sets of cartridges, US/ROW, EMEA, and AP. Each time a cartridge is inserted into the printer it reads the region of the cartridge and sets the device to that region. If the customer buys a cartridge from another region that does not match the printer's region then the printer's region will need to be reset from this menu.</p> <p>Only available on 4 inch control panels models.</p> |